


Steckanschlüsse und Zubehör

3126 Blindstopfen

Technisches Polymer




ØD		G	L	L1	Kg
3	3126 03 00	6	25	13,5	0,001
4	3126 04 00	4	30	15,5	0,001
6	3126 06 00	8	33	16,5	0,001
8	3126 08 00	10	35	17,5	0,001
10	3126 10 00	12	42	21	0,002
12	3126 12 00	14	45	22	0,003
14	3126 14 00	16	49	23,5	0,005
16	3126 16 00*	19	57	30	0,064

*Messing vernickelt

3126 Blindstopfen

Zöllig

Technisches Polymer




ØD		G	L	L1	Kg
1/4	3126 56 00	8	36,5	22	0,001
3/8	3126 60 00	12	42	22	0,002
1/2	3126 62 00	15	48,5	21,5	0,003

Zusätzliche Anschlüsse: 5/32" (4mm) und 5/16" (8 mm)

3122 Steckadapter-Schlauchtülle


Technisches Polymer



ØD1	ØD2		ØD3	L	L1	L2	Kg
4	3,2	3122 04 53	5	37	25	17	0,004
	5	3122 04 05	7	37	25	17	0,005
6	5	3122 06 05	7	39	25	17	0,001
	6,3	3122 08 56	8,5	39,5	21	17	0,001
8	8	3122 08 08	10	44,5	26	22	0,001
	6,3	3122 10 56	8	45	24,5	17	0,002
10	8	3122 10 08	10	50	29,5	22	0,002
	8	3122 12 08	10	50	26	22	0,002
12	10	3122 12 10	12	48,5	25,5	22,5	0,002
	12,5	3122 12 62	14,5	57	34	22,5	0,004
14	12,5	3122 14 62	14,5	59,5	34,5	22,5	0,022

3151 Verschlussstopfen

Technisches Polymer, NBR



ØD		G	H	Kg
4	3151 04 00	8,5	15	0,001
6	3151 06 00	10,5	17	0,001
8	3151 08 00	13,5	22	0,003
10	3151 10 00	16	22	0,003
12	3151 12 00	19	28	0,005
14	3151 14 00	22	31	0,009

Weitere Produkte auf Anfrage erhältlich. Sprechen Sie uns bitte an.